



## INTRODUCTION

**Daddy's Eye** is a powerful logger incoming/outgoing SMS and voice calls for Symbian Series 60 3<sup>rd</sup> and 5<sup>th</sup> Edition devices. Recorded activities are uploaded to your E-mail. Registered application can upload activities to their Daddy's Eye account with showing location on a map. You can login to your account to view the logs at the Daddy's Eye Reports server.

The Daddy's Eye can work in stealth mode. It is not listed at “Installed Applications”.

## CAPABILITIES

- simple adjusting;
- remote control by SMS;
- beep suppression while call recording (some phones may still have the beep);
- recording with low weight AMR format;
- automatic uploading intercepted SMS and calls on E-mail or Daddy's Eye account;
- environment recording;
- showing location of intercepted events on the map;
- stealth mode;
- autostart after phone rebooting;
- PIN code protection;
- scheduled activities uploading;

## INSTALLING

The application should be installed in the same way as all Symbian applications. Transfer the application to your phone via USB cable, Bluetooth, etc., or download application direct to the phone and you will suggested automatically install the application. Install it to your internal device memory for optimum performance. After you have installed the “Daddy's Eye” it will be launched automatically.

The application doesn't have an icon in “Installed applications” folder. If “Daddy's Eye” installed successfully it should start automatically. When the application in background you can open it just dialing \*#000000 then press call, then press hangup. “000000” is default pin code. You can change it.

If you closed the application you should restart the phone or reinstall the application to start it again.

## UNINSTALLING

To uninstall the application, go to the App. Manager, select DBackup and choose “Options->Remove”. **If you changed PIN from 000000 to other you will be asked to enter the PIN during uninstalling. You should enter the right PIN to remove the application otherwise it will be failed.**

<http://www.daddyseye.com>

## REGISTRATION

Daddy's Eye is full functional by defaults. There are free 5 days for a trial period.

After 5 days expired the application continue working, but reminder of the subscription will be sent instead of reports to your e-mail;

Go to <http://www.daddyseye.com/buy.html> to purchase subscription in your browser.

**COUTION:** you should provide IMEI code of the phone you will install the application on.

## FIRST START

After installation the application will be started automatically. The version, IMEI and current Internet Access Point are displayed on main window.

### ***Application Operation***

«Options» - opens application menu.

«Hide» - sends the application to background.

To bring to foreground the application dial **\*#pin-code** then press call key, then press hangup key.

Default pin-code is **000000**. Or send SMS: **#:pin-code:show**

You should enter your e-mail address and select Internet Access Point at first start. Otherwise you wouldn't be able to hide the application. You will receive e-mail with your “Daddy's Eye” account data after Internet Access Point selected.

## APPLICATION MENU

Application menu contents three items:

- Settings
- Select Access Point
- Exit

«Settings» - opens application settings list.

«Select Access Point» - selects Internet Access Point.

«Exit» - exits the application.

Please note: after exiting the application to restart it you should reboot the phone or reinstall the application.

## SETTINGS

There are not many settings needed to application work:

“PIN” - six digits secret code. It is used to access to application by dialing *\*#pin-code#*. Default is 000000.

**CAUTION:** If you changed PIN from 000000 to other you will be asked to enter the PIN during uninstalling. You should enter the right PIN to remove the application otherwise it will be failed.

“Hide in tasklist” - enable/disable hiding the application in tasklist.

“Autostart” - enable/disable autostart the application after phone rebooting.

“Record voice calls” - enable/disable voice call recording.

“Recording quality” - sets recording quality. If the phone “beeps” during recording, try to decrease the quality.

“Send via” - activities log upload method.

<http://www.daddyseye.com>

Next setting item depends on “Send via” value (it may be E-mail address or nothing if “Send via” is HTTP).

“Upload mode” - might be “After event” , “Scheduled” or “Every half hour”. If it is set to “Scheduled” you would be able to set the hour when all activities are sent. If it is set to “After event” reports will be sent just after the call, SMS or when environment recording is done. If it is set to “Every half hour” reports will be sent every 30 minutes.

## SMS COMMANDS

You can control the application remotely by SMS commands. Command is sent to a phone with Daddy's Eye in follow format:

**[#:pin-code:command \[params\]](#)**

For example, to stop the application the SMS will be (pin-code is default 000000):

**[#:000000:stop](#)**

another example, set "Send via" mode to E-mail:

**[#:000000:email address@mail.com](#)**

If SMS command is successful you will receive SMS with "OK" text. If the command failed to succeed or the pin-code is incorrect you will receive SMS with "ERROR" text.

***SMS commands list:***

<b>stop</b>	stops the application. Messages and calls are not intercept.
<b>start</b>	starts the application.
<b>email</b>	sets “Send via” to E-mail. The E-mail address is an optional parameter of the command. If parameter is absent the E-mail address provided early is used.
<b>http</b>	sets “Send via” to HTTP. The command has no parameter.
<b>recordon</b>	enable voice calls recording
<b>recordoff</b>	disable voice calls recording
<b>show</b>	brings the application to foreground

<http://www.daddyseye.com>

<b>recenv</b>	starts environment recording. The command has a parameter – record duration. It should be from 1 to 35 minutes. Ex.: <b>#:000000:recenv 15</b>
<b>uplmode</b>	sets upload mode. The parameter is 0 or 1. 0 – upload mode is after event. 1 – upload mode is scheduled
<b>uptime</b>	sets upload time. The parameter is from 0 to 23.
<b>sendnow</b>	sends all reports without waiting schedule time.



## User Guide

<http://www.daddyseye.com>

IT Systems LLC



## User Guide

<http://www.daddyseye.com>

<http://www.daddyseye.com>